

## FEELUX Surface mounted LED Luminaire 100-240V~, 50/60Hz, CRI 90 TUNELIGHT2 LED Spot Free CRI90



**Type** TUN7 xxK -UNV-C90(-S) 0.07A, 7W (xx=LED Color Temperature, S=Switch type)  
 TUN11 xxK -UNV-C90(-S) 0.11A, 10W  
 TUN15 xxK -UNV-C90(-S) 0.15A, 15W



This LED Luminaire is designed for universal usage in shop constructions, counters, shelves, display units, concealed lightings, and etc. Continuous row lightings are to be connected through flexible/direct connector and power supply cord

Class of protection II  
 Degree of protection IP 20  
 Radio-interference-suppressed

### Mounting Dimensions



TUNELIGHT2 Spot Free		Wattage	Kelvin	Length L
ORIGINAL	SWITCH TYPE			
TUN7 xxK-UNV-C90 (xx=22,25,27,30,35,40,60)	TUN7 xxK-UNV-C90-S (xx=22,25,27,30,35,40,60)	7W	22 : 2200K 25 : 2500K 27 : 2700K 30 : 3000K 35 : 3500K 40 : 4000K 60 : 6000K	526 mm
TUN11 xxK-UNV-C90 (xx=22,25,27,30,35,40,60)	TUN11 xxK-UNV-C90-S (xx=22,25,27,30,35,40,60)	11W		836 mm
TUN15 xxK-UNV-C90 (xx=22,25,27,30,35,40,60)	TUN15 xxK-UNV-C90-S (xx=22,25,27,30,35,40,60)	15W		1145 mm

Fig.1 MAIN

### Mounting Arrangements





Fig.2 Mounting

### Installation



**CAUTION** Risk of Fire,  
 Max. wattage in one lighting row is : **400 Watts**  
 Max. permitted ambient temperature : **50 °C**  
 Input connector of TUNPC must be firmly inserted in Luminaire.

The direction of the supply must be observed prior to installation (IN-Input connector...OUT-Output connector). Fixing of the LED Luminaire takes place via mounting clips/magnets. These must be fixed at the desired area with screw(s), then the LED Luminaire can be snapped in place. Insert the end cap to the last luminaire of one lighting row

### WARNING Information

This lighting is for indoor use only. Installation and removal must be performed after power supply disconnected. Installation shall be performed by a qualified electrician understanding the construction and operation of this lighting system and the electrical requirements involved. When connecting, insert connectors firmly. Pay close attention to the IN-Male...OUT-Female figures in lighting. Meaning of crossed out wheeled dustbin: Do not dispose electrical appliances as unsorted municipal waste, use designated collection facilities. Contact local government for information regarding available collection systems. If electrical appliances are disposed in landfills, hazardous substances/materials can leak into the groundwater, and obstruct food chain, damaging your health and well being. When replacing old appliances with new ones, the retailer is legally responsible for taking back old appliance for disposal with free of charge. Do not make modifications to or alter lighting housing, driver enclosure or electrical components other than those required for proper installation.

No part of this publication may be reproduced without the prior permission of the publishers.

### CAUTION Information

The unit conforms to the electromagnetic compatibility directive 2014/30/EU, and low voltage directive 2014/35/EU  
 ! RISK OF FIRE (ATTENTION – RISQUE D'INCENDIE)  
 ! SUITABLE FOR DAMP LOCATIONS (CONVIENT AUX EMPLACEMENTS HUMIDES)  
 ! SUITABLE FOR UNDER-CABINET MOUNT (PEUT ÊTRE FIXÉ SOUS UNE ARMOIRE)  
 ! SUITABLE FOR INSTALLATION IN THE STORAGE AREA OF A CLOTHES CLOSET (APPROPRIÉ POUR L'INSTALLATION DANS LA ZONE DE STOCKAGE D'UN PLACARD)  
 ! INDOOR USE ONLY  
 ! LED light may be bright and intense enough to cause injury to human eyes. The customer should never look directly into the LED light.